

What is claimed is:

1           1. A circuit arrangement for use in communicating multiple signals over a  
2 common signal path between first and second clock domains during hardware-based  
3 logic emulation, wherein the first clock domain is emulated via a first multi-step  
4 evaluation cycle and the second domain is emulated via a second multi-step  
5 evaluation cycle, the circuit arrangement comprising:

6                   (a) a buffer interposed in a common signal path between first and  
7 second clock domains, the buffer including first and second locations, the first  
8 location associated with a first evaluation step in the first multi-step evaluation  
9 cycle and a first evaluation step in the second multi-step evaluation cycle, and  
10 the second location associated with a second evaluation step in the first multi-  
11 step evaluation cycle and a second evaluation step in the second multi-step  
12 evaluation cycle; and

13                   (b) logic circuitry coupled to the buffer, the logic circuitry configured  
14 to store in the first location of the buffer a first time-multiplexed signal output  
15 over the common signal path by the first clock domain during the first  
16 evaluation step in the first multi-step evaluation cycle, and to store in the  
17 second location of the buffer a second time-multiplexed signal output over the  
18 common signal path by the first clock domain during the second evaluation  
19 step in the first multi-step evaluation cycle, the logic circuit further configured  
20 to output the first time-multiplexed signal stored in the first location over the  
21 common signal path to the second clock domain during the first evaluation  
22 step in the second multi-step evaluation cycle, and to output the second time-  
23 multiplexed signal stored in the second location over the common signal path  
24 to the second clock domain during the second evaluation step in the second  
25 multi-step evaluation cycle.

1           2. The circuit arrangement of claim 1, wherein the buffer comprises a multi-  
2 port array including a write port and a read port, and wherein the logic circuitry  
3 comprises a write control circuit and a read control circuit respectively coupled to the  
4 write port and read port of the multi-port array, the write control circuit configured to

5 control storage of signals from the first clock domain in the multi-port array, and the  
6 read control circuit configured to control output of signals from the multi-port array to  
7 the second clock domain.

1 3. The circuit arrangement of claim 2, wherein each of the write and read  
2 control circuits includes a counter.

1 4. The circuit arrangement of claim 3, wherein the counter in the write control  
2 circuit is configured to be incremented during each evaluation step in the first multi-  
3 step evaluation cycle, and wherein the counter in the read control circuit is configured  
4 to be incremented during each evaluation step in the second multi-step evaluation  
5 cycle.

1 5. The circuit arrangement of claim 4, wherein the counter in the write control  
2 circuit is configured to be reset for each first multi-step evaluation cycle, and wherein  
3 the counter in the read control circuit is configured to be reset for each second multi-  
4 step evaluation cycle.

1 6. The circuit arrangement of claim 4, wherein the counter in the first multi-  
2 step evaluation cycle maintains a current evaluation step number for the first clock  
3 domain, wherein the counter in the second multi-step evaluation cycle maintains a  
4 current evaluation step number for the second clock domain, wherein the read and  
5 write control circuits are each configured to use the respective current evaluation step  
6 numbers stored in the respective counters to address the multi-port array.

1 7. The circuit arrangement of claim 1, wherein the first and second multi-step  
2 evaluation cycles have different numbers of evaluation steps from one another.

1 8. The circuit arrangement of claim 1, wherein the buffer is further interposed  
2 within a second common signal path between the first and second clock domains, and  
3 wherein the logic circuitry is further configured to store in the buffer time-multiplexed

4 signals output over the second common signal path by the first clock domain  
5 concurrently with storing time-multiplexed signals output over the first common  
6 signal path, and to output over the second common signal path from the buffer to the  
7 second clock domain, the time-multiplexed signals stored in the buffer.

1 9. The circuit arrangement of claim 1, wherein the first and second locations  
2 are each a plurality of bits wide, wherein the buffer is interposed within a multi-bit  
3 common signal path between the first and second clock domains, and wherein the  
4 logic circuitry is further configured to stored in the buffer multi-bit time-multiplexed  
5 signals output over the multi-bit common signal path by the first clock domain, and to  
6 output over the multi-bit common signal path from the buffer to the second clock  
7 domain, the multi-bit time-multiplexed signals stored in the buffer.

1 10. A logic board comprising the circuit arrangement of claim 9.

1 11. A logic emulator comprising the circuit arrangement of claim 9.

1 12. The logic emulator of claim 11, further comprising a plurality of  
2 emulation processor integrated circuit devices, at least one of the emulation processor  
3 integrated circuit devices configured to emulate the first clock domain, and at least  
4 one other of the emulation processor integrated circuit devices configured to emulate  
5 the second clock domain.

1 13. The logic emulator of claim 12, further comprising a plurality of logic  
2 boards, each including a subset of the plurality of emulation processors, and wherein  
3 the common signal path extends between emulation processors disposed on different  
4 logic boards.

1           14. A circuit arrangement for use in communicating multiple signals over a  
2 common signal path between first and second clock domains during hardware-based  
3 logic emulation, wherein the first clock domain is emulated using a first multi-step  
4 evaluation cycle and the second domain is emulated using a second multi-step  
5 evaluation cycle, the circuit arrangement comprising:

6                   (a) a buffer interposed between the first and second clock domains  
7 within the common signal path, the buffer including a plurality of locations,  
8 each of which associated with an evaluation step from each of the first and  
9 second multi-step evaluation cycles;

10                   (b) a write control circuit responsive to a first step signal associated  
11 with a current evaluation step in the first multi-step evaluation cycle, the write  
12 control circuit configured to store a signal output over the common signal path  
13 by the first clock domain in a location in the buffer that is associated with the  
14 current evaluation step in the first multi-step evaluation cycle; and

15                   (c) a read control circuit responsive to a second step signal associated  
16 with a current evaluation step in the second multi-step evaluation cycle, the  
17 read control circuit configured to output a signal stored in a location in the  
18 buffer that is associated with the current evaluation step in the second multi-  
19 step evaluation cycle.

1           15. The circuit arrangement of claim 14, wherein the buffer comprises a  
2 multi-port array including a write port coupled to the write control circuit and a read  
3 port coupled to the read control circuit, wherein the write control circuit includes a  
4 counter configured to be incremented in response to the first step signal, and wherein  
5 the read control circuit includes a counter configured to be incremented in response to  
6 the second step signal.

1           16. The circuit arrangement of claim 15, wherein the counter in the write  
2 control circuit is configured to be reset for each first multi-step evaluation cycle, and  
3 wherein the counter in the read control circuit is configured to be reset for each second  
4 multi-step evaluation cycle.

1           17. The circuit arrangement of claim 15, wherein the counter in the first multi-  
2 step evaluation cycle maintains a current evaluation step number for the first clock  
3 domain, wherein the counter in the second multi-step evaluation cycle maintains a  
4 current evaluation step number for the second clock domain, wherein the read and  
5 write control circuits are each configured to use the respective current evaluation step  
6 numbers stored in the respective counters to address the multi-port array.

1           18. The circuit arrangement of claim 14, wherein the first and second multi-  
2 step evaluation cycles have different numbers of evaluation steps from one another.

IBM, the IBM logo, and the "Think" logo are trademarks of International Business Machines Corporation. All other marks are the property of their respective owners.

1           19. A method of communicating multiple signals over a common signal path  
2 between first and second clock domains during hardware-based logic emulation, the  
3 method comprising:

4                   (a) during each of a first plurality of evaluation steps in an evaluation  
5 cycle for the first clock domain, communicating a signal associated with such  
6 evaluation step across the common signal path from the first clock domain to a  
7 buffer that has a plurality of locations, and storing the communicated signal in  
8 a location among the plurality of locations in the buffer that is associated with  
9 such evaluation step; and

10                   (b) during each of a second plurality of evaluation steps in an  
11 evaluation cycle for the second clock domain, wherein each of the second  
12 plurality of evaluation steps is associated with a location among the plurality  
13 of locations, communicating a signal from the location in the buffer that is  
14 associated with such evaluation step from the second plurality of evaluation  
15 steps to the second clock domain.

1           20. The method of claim 19, wherein communicating the signal associated  
2 with each evaluation step in the evaluation cycle for the first clock domain includes  
3 incrementing a first counter for each such evaluation step, and wherein  
4 communicating the signal from the location associated with each evaluation step in  
5 the evaluation cycle for the second clock domain includes incrementing a second  
6 counter for each such evaluation step.

1           21. The method of claim 20, further comprising resetting the first counter for  
2 each evaluation cycle for the first clock domain, and resetting the second counter for  
3 each evaluation cycle for the second clock domain.

1           22. A method of communicating multiple signals over a common signal path  
2 between first and second clock domains during hardware-based logic emulation,  
3 wherein the first clock domain is emulated via a first multi-step evaluation cycle that  
4 includes first and second evaluation steps and the second domain is emulated via a  
5 second multi-step evaluation cycle that includes first and second evaluation steps, the  
6 method comprising:

7           (a) during the first evaluation step in the first multi-step evaluation  
8 cycle, receiving a first time-multiplexed signal output over the common signal  
9 path by the first clock domain and storing the first time-multiplexed signal in a  
10 first location in a buffer interposed in the common signal path, wherein the  
11 first location is associated with the first evaluation step in the first multi-step  
12 evaluation cycle and the first evaluation step in the second multi-step  
13 evaluation cycle;

14           (b) during the second evaluation step in the first multi-step evaluation  
15 cycle, receiving a second time-multiplexed signal output over the common  
16 signal path by the first clock domain and storing the second time-multiplexed  
17 signal in a second location in the buffer, wherein the second location is  
18 associated with the second evaluation step in the first multi-step evaluation  
19 cycle and the second evaluation step in the second multi-step evaluation cycle;

20           (c) during the first evaluation step in the second multi-step evaluation  
21 cycle, communicating the first time-multiplexed signal stored in the first  
22 location over the common signal path to the second clock domain; and

23           (d) during the second evaluation step in the second multi-step  
24 evaluation cycle, communicating the second time-multiplexed signal stored in  
25 the second location over the common signal path to the second clock domain.  
26

1           23. The method of claim 22, wherein the buffer comprises a multi-port array  
2 including a write port and a read port, the method further comprising incrementing a  
3 first counter for each evaluation step in the first multi-step evaluation cycle,  
4 incrementing a second counter for each evaluation step in the second multi-step

24. The method of claim 20, further comprising resetting the first counter for each first multi-step evaluation cycle, and resetting the second counter for each second multi-step evaluation cycle.